

KOHLER®

SDMO®



HX 3000 C

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 3000 C

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	98
Acoustic pressure level @1m in dB(A)	84
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX200
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	196
Oil system capacity including filters (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661

KOHLER®
SDMO®

4/18/2018

HX 3000 C - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R01 This set includes the hour meter and the differential circuit breaker.



R05M The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



R06 Trolley kit for 2 and 3 kW generating sets.



RBH1 Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5 Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RHO Cover for SDMO 's generating sets, welding sets and water pumps



RPM Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.