



## PERFORM 5500 T

PORTABLE POWER

Generating Sets Range PERFORM

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Compact frame with protection panels against shocks
- Good value for money
- Starting up facilitated thanks to the summer/winter positions

**QUAD CLEAN AIR FILTER** The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

### Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



This product meets the Qualigen charter, which aims to a level of quality and guarantee the safety of users. Qualigen commitment to safety and quality.

## PERFORM 5500 T

### GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW) *	4.50
Max power (kVA)	5.60
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	7.30
75% cons. (l/h) *	1.70
75% Autonomy (h) *	4.30
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	68

### ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH395
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	277
Oil system capacity including filters (L)	1.10

### ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 400V 16A socket - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	71
Width (cm)	55.50
Height (cm)	49
Dry Weight (kg)	73.50

### PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49.50
Weight (kg)	75.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	463

### ACCESSORIES SUPPLIED




Funnel
Floor maintaining slot



User and maintenance manual
Ergonomic handle grip

### OPTIONS



<b>R03</b>	This set includes the hour meter and the differential circuit breaker.
------------	--



<b>RKB1HD</b>	Trolley kit for the generating sets of 6kW or below
---------------	---



<b>RKS2</b>	Maintenance kit for KOHLER CH395 and CH440 engines.
-------------	---



<b>RH1</b>	Cover for SDMO 's generating sets, welding sets and water pumps
------------	---



<b>RPM</b>	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
------------	---



<b>RPQ</b>	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.
------------	--