



## DIESEL 6000 E XL C

PORTABLE POWER

Generating Sets Range DIESEL

#### **PRODUCT ADVANTAGES**

- · Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Large Autonomy
- Comfort of prehension thanks to the ergonomic handles
- · Electric starter with batteries without maintenance

OIL SAFETY Thanks to this functionality, the engine will not start or will stop during its functioning if the oil level for gasolines or the oil pression for diesels is to low: your generating set is perfectly protected!

#### Range DIESEL

Both long run times and very long life for professional applications.

















# **DIESEL 6000 E XL C**

#### **GENERAL SPECIFICATIONS**

Range	DIESEL
Frequency (Hz)	50 Hz
Max power (kW) *	5.20
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	16
75% cons. (I/h) *	1.20
75% Autonomy (h) *	13.30
Sound power level guaranteed LwA dB(A)	108
Acoustic pressure level @1m in dB(A)	93
Acoustic pressure level @7m in dB(A)	79

### **ENGINE SPECIFICATIONS**

Engine brand	KOHLER DIESEL
Engine type	KD440E
Distribution	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm3)	442
Oil system capacity including filters (L)	1.50

#### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 21
Insulation class	Н

#### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

#### **DIMENSIONS AND WEIGHT**

Length (cm)	81
Width (cm)	55.50
Height (cm)	59
Dry Weight (kg)	103

#### **PACKAGING**

Packaging type	Box
Length (cm)	82
Width (cm)	56.50
Height (cm)	60
Weight (kg)	106
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	646





# DIESEL 6000 E XL C

## **ACCESSORIES SUPPLIED**



User and maintenance manual



Floor maintaining slot



Ergonomic handle grip

**RPQ** 



For earthing your generator set. Galvanised 1 m long spike, supplied with 2

m of 10 mm<sup>2</sup> cable.

Battery without maintenance

	R02	This set includes the hour meter and the differential circuit breaker.
	R05M	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
	RKB1HD	Trolley kit for the generating sets of 6kW or below
	RKDS1	Maintenance kit for KOHLER CH350E and CH440E engines (Diesel 6000 E XL C - Diesel 6500 TE XL C).
Street, Street	RH1	Cover for SDMO 's generating sets, welding sets and water pumps
6	RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V

