



HX 4000

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 4000

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	4
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	5.30
75% cons. (l/h) *	2.10
75% Autonomy (h) *	2.50
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	82
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX270
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	270
Oil system capacity including filters (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	71.50
Width (cm)	57
Height (cm)	49
Dry Weight (kg)	56

PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49.50
Weight (kg)	58.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	361

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R01

This set includes the hour meter and the differential circuit breaker.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB2

Trolley kit for the generating sets superior to 6kW



R33

Maintenance kit for Honda GX270



RH1

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.