

# KOHLER®

# SDMO®



## HX 6000 C

PORTABLE POWER

Generating Sets Range INTENS

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HX 6000 C

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	6
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6.10
75% cons. (l/h) *	2.50
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	100
Acoustic pressure level @1m in dB(A)	86
Acoustic pressure level @7m in dB(A)	72

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX390
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	389
Oil system capacity including filters (L)	1.10

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 21
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	71.50
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	75

### PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	59.50
Weight (kg)	77.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	475

**KOHLER®**  
**SDMO®**

5/3/2018

HX 6000 C - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

# KOHLER®

# SDMO®

## HX 6000 C

### ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

### OPTIONS



**R02**

This set includes the hour meter and the differential circuit breaker.



**R05M**

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



**RKB2**

Trolley kit for the generating sets superior to 6kW



**RH1**

Cover for SDMO 's generating sets, welding sets and water pumps



**RPM**

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V

# KOHLER® SDMO®

5/3/2018

HX 6000 C - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervem - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com