



## PERFORM 3000 GAZ

PORTABLE POWER

Generating Sets Range PERFORM

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Dual-fuel unleaded petrol or LPG
- Compact frame with protection panels against shocks
- Starting up facilitated thanks to the summer/winter positions

**QUAD CLEAN AIR FILTER** The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime  
This genset features a bi-fuel engine, meaning that it can run on either unleaded gas or LPG simply by moving the fuel supply lever (closed: LPG; open: gas).

### Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.

## PERFORM 3000 GAZ

### GENERAL SPECIFICATIONS

Range	PERFORM	
Frequency (Hz)	50 Hz	
Nominal voltage (V)	230	
Number of Phase	Single phase	
Fuel	Petrol	LPG
Max power (kW) *	3	2.40
Tank (L)	4.10	-
75% cons. (l/h) *	1.30	-
75% Autonomy (h) *	3.20	-
Sound power level guaranteed LwA dB(A)	96	
Acoustic pressure level @1m in dB(A)	82	
Acoustic pressure level @7m in dB(A)	68	

### ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH270
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	208
Oil system capacity including filters (L)	0.60

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	65
Width (cm)	51
Height (cm)	46
Dry Weight (kg)	46.50

### PACKAGING

Packaging type	Box
Length (cm)	66
Width (cm)	52.50
Height (cm)	47
Weight (kg)	48.50
Pallet type	140/110
Number of box by pallet	12
Pallet height (cm)	154
weight of the packaged Pallet (kg)	598



4/18/2018

PERFORM 3000 GAZ - PORTABLE POWER - Generating Sets PERFORM

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen's commitment to safety and quality.

### ACCESSORIES SUPPLIED



Funnel
Floor maintaining slot



User and maintenance manual
Ergonomic handle grip

### OPTIONS



<b>R01</b>	This set includes the hour meter and the differential circuit breaker.
------------	--



<b>R05M</b>	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
-------------	---



<b>RKB1HD</b>	Trolley kit for the generating sets of 6kW or below
---------------	---



<b>RKS1</b>	Maintenance kit for KOHLER CH270 engine.
-------------	--



<b>RHO</b>	Cover for SDMO 's generating sets, welding sets and water pumps
------------	---



<b>RPM</b>	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
------------	---



<b>RPQ</b>	For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm <sup>2</sup> cable.
------------	--



<b>RBAC</b>	Removable storage box
-------------	-----------------------



<b>RKD1</b>	kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral
-------------	---