



TECHNIC 20000TE AVR C

PORTABLE POWER

Generating Sets Range TECHNIC

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- AVR : Automatic tension regulation
- Electric starter with batteries without maintenance
- Large Autonomy

The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature AVR By regulating the voltage electronically by $\pm 2\%$, depending on the model, the AVR eliminates all risk of damage to boilers or certain kinds of electronic equipment.

Range TECHNIC

A long run time equipment that can withstand extreme conditions, for daily professional use.



TECHNIC 20000TE AVR C

GENERAL SPECIFICATIONS

Range	TECHNIC
Frequency (Hz)	50 Hz
Max power (kW) *	15.20
Max power (kVA)	19
Nominal voltage (V)	400
Number of Phase	Three phase
Fuel	Petrol
Tank (L)	35
75% cons. (l/h) *	5.60
75% Autonomy (h) *	6.30
Sound power level guaranteed LwA dB(A)	104
Acoustic pressure level @1m in dB(A)	88
Acoustic pressure level @7m in dB(A)	74

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH940
Distribution	O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm ³)	999
Oil system capacity including filters (L)	2.75

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	Yes
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE


1 230V 10/16A socket - circuit breaker + 2 400V 16A sockets - circuit breaker + 1 400V 32A socket - circuit breaker + hour meter + indicator + APM202

DIMENSIONS AND WEIGHT

Length (cm)	94.50
Width (cm)	57
Height (cm)	90
Dry Weight (kg)	188

PACKAGING

Packaging type	Box / Pallet
Length (cm)	96
Width (cm)	58.50
Height (cm)	105
Weight (kg)	201
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0



5/18/2018

TECHNIC 20000TE AVR C - PORTABLE POWER - Generating Sets TECHNIC

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 – France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



Funnel
Battery without maintenance



User and maintenance manual
Hour meter

OPTIONS



R03B	This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.
-------------	---



RSTART2	Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)
----------------	--



VERSO50	Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.
----------------	---



RKB2	Trolley kit for the generating sets superior to 6kW
-------------	---



RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V
------------	---