



DIESEL 6000 E SILENCE

PORTABLE POWER

Generating Sets Range DIESEL

PRODUCT ADVANTAGES

- · Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Very Silent
- Connection interface equipped with an hour meter
- Hydrocarbons bulk tank

This genset is quiet and compact and features easyto-reach components for simplified maintenance. The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature

Range DIESEL

Both long run times and very long life for professional applications.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

DIESEL 6000 E SILENCE

GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50 Hz
Max power (kW) *	5.20
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	27
75% cons. (I/h) *	1.20
75% Autonomy (h) *	22.50
Sound power level guaranteed LwA dB(A)	92
Acoustic pressure level @1m in dB(A)	76
Acoustic pressure level @7m in dB(A)	63

ENGINE SPECIFICATIONS

Engine brand	KOHLER DIESEL
Engine type	KD15-440E
Distribution	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm3)	442
Oil system capacity including filters (L)	1.50

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 21
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator + APM202

DIMENSIONS AND WEIGHT

Length (cm)	99
Width (cm)	61.50
Height (cm)	96
Dry Weight (kg)	198

PACKAGING

Packaging type	Box
Length (cm)	101
Width (cm)	63
Height (cm)	94
Weight (kg)	201
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0





DIESEL 6000 E SILENCE

ACCESSORIES SUPPLIED



User and maintenance manual



Lifting eye



Battery without maintenance

Hour meter

OPTIONS

	R02B	This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.
	RSTART2	Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)
	VERSO50	Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.
	R05M	The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.
00	RKB3	Trolley kit with 1 handle and 2 solid tyres for Diesel 6000 E SILENCE and Diesel 6500 TE SILENCE gensets
	RKDS2	Maintenance kit for KOHLER KD440E engine (Diesel 6000 E Silence - Diesel 6500 TE Silence)
	Adaptor for industrial sockets	ERR:not found in dict valeurs
	RPM	Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V

