



TECHNIC 6500 E AVR UK M

PORTABLE POWER

Generating Sets Range TECHNIC

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Connection interface equipped with an hour meter and the APM202 control unit
- Electric starter with batteries without maintenance
- AVR : Automatic tension regulation

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

Range TECHNIC

A long run time equipment that can withstand extreme conditions, for daily professional use.

TECHNIC 6500 E AVR UK M

GENERAL SPECIFICATIONS

Range	TECHNIC
Frequency (Hz)	50 Hz
Max power (kW) *	6.50
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	18
75% cons. (I/h) *	2.60
75% Autonomy (h) *	6.90
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH440E
Distribution	O.H.V.
Start	Electrical Starter
Oil shutdown	Oui
Displacement (cm3)	429
Oil system capacity including filters (L)	1.30

ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	Yes
Indication of protection	IP 23
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55.50
Height (cm)	59
Dry Weight (kg)	101

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56.50
Height (cm)	60
Weight (kg)	104
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	634





This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety or users. Qualigen: commitment to safety and quality.






TECHNIC 6500 E AVR UK M

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual



Ergonomic handle grip



Battery without maintenance

Floor maintaining slot



RSTART2

Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)



VERSO₅₀

Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.



RKB1HD

Trolley kit for the generating sets of 6kW or below



RKS2

Maintenance kit for KOHLER CH395 and CH440 engines.



R50

16A blue 230V male plug - Sold per 1 or 10



R51

16A yellow 115V male plug - Sold per 1 or 10



R52

32A blue 230V male plug - Sold per 1 or 5



R53

32A yellow 115V male plug - Sold per 1 or 5



R54

Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3



