



PERFORM 4500 GAZ TB UK

PORTABLE POWER

Generating Sets Range PERFORM

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Dual-fuel unleaded petrol or LPG
- Compact frame with protection panels against shocks
- Starting up facilitated thanks to the summer/winter positions

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

This genset features a bi-fuel engine, meaning that it can run on either unleaded gas or LPG simply by moving the fuel supply lever (closed: LPG; open: gas).

Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.

PERFORM 4500 GAZ TB UK

GENERAL SPECIFICATIONS

Range	PERFORM	
Frequency (Hz)	50 Hz	
Nominal voltage (V)	230	
Number of Phase	Single phase	
Fuel	Petrol	LPG
Max power (kW) *	4.20	3.90
Tank (L)	7.30	-
75% cons. (l/h) *	1.70	-
75% Autonomy (h) *	4.30	-
Sound power level guaranteed LwA dB(A)	97	
Acoustic pressure level @1m in dB(A)	83	
Acoustic pressure level @7m in dB(A)	69	

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine ref.	CH395
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	277
Oil system capacity including filters (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 115V 32A socket - circuit breaker + 1 230V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55.50
Height (cm)	59
Dry Weight (kg)	63.50

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56.50
Height (cm)	60
Weight (kg)	65.50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	403



4/27/2018

PERFORM 4500 GAZ TB UK - PORTABLE POWER - Generating Sets PERFORM

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen's commitment to safety and quality.

ACCESSORIES SUPPLIED



Funnel
Floor maintaining slot



User and maintenance manual
Ergonomic handle grip

OPTIONS



RKB1HD	Trolley kit for the generating sets of 6kW or below
---------------	---



RKS2	Maintenance kit for KOHLER CH395 and CH440 engines.
-------------	---



R50	16A blue 230V male plug - Sold per 1 or 10
------------	--



R51	16A yellow 115V male plug - Sold per 1 or 10
------------	--



R53	32A yellow 115V male plug - Sold per 1 or 5
------------	---



R54	Adaptator R54 16A/13A adaptor unit. Sold per 1 or 3
------------	---



R55	ADAPTATOR R55 16A/13A adaptor economy. Sold per 1 or 3
------------	--



R56	ADAPTATOR R56 16A/13A double adaptor. Sold per 1 or 3
------------	---



RH1	Cover for SDMO 's generating sets, welding sets and water pumps
------------	---



RBAC

Removable storage box