



PERFORM 4500 TB UK

PORTABLE POWER

Generating Sets Range PERFORM

PRODUCT ADVANTAGES

- · Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Compact frame with protection panels against shocks
- Good value for money
- Starting up facilitated thanks to the summer/winter positions

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



















This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety or users. Qualigen: commitment to safety and quality.

PERFORM 4500 TB UK

GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW) *	4.20
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	7.30
75% cons. (I/h) *	1.70
75% Autonomy (h) *	4.30
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	68

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH395
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	277
Oil system capacity including filters (L)	1.10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 115V 32A socket - circuit breaker + 1 230V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	71
Width (cm)	55.50
Height (cm)	49
Dry Weight (kg)	62

PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	55
Height (cm)	49.50
Weight (kg)	64
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	394





PERFORM 4500 TB UK

ACCESSORIES SUPPLIED



Funnel

RH1

Floor maintaining slot



User and maintenance manual

Ergonomic handle grip

OPTIONS



RKB1HD Trolley kit for the generating sets of 6kW or below



RKS2 Maintenance kit for KOHLER CH395 and CH440 engines.



Cover for SDMO 's generating sets, welding sets and water pumps

