

# KOHLER®

# SDMO®



## HX 2500 UK

PORTABLE POWER

Generating Sets Range INTENS

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## HX 2500 UK

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	2.20
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	0.90
75% Autonomy (h) *	3.40
Sound power level guaranteed LwA dB(A)	94
Acoustic pressure level @1m in dB(A)	80
Acoustic pressure level @7m in dB(A)	65

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX160
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	163
Oil system capacity including filters (L)	0.60

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 230V 16A socket - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	39

### PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	41
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	631

**KOHLER®**  
**SDMO®**

3/13/2018

HX 2500 UK - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

### ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

### OPTIONS



**R18** Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)



**R50** 16A blue 230V male plug - Sold per 1 or 10



**R51** 16A yellow 115V male plug - Sold per 1 or 10



**R54** Adaptator R54 16A/13A adaptor unit. Sold per 1 or 3



**R55** ADAPTATOR R55 16A/13A adaptor economy. Sold per 1 or 3



**R56** ADAPTATOR R56 16A/13A double adaptor. Sold per 1 or 3



**RBH1** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



**RBH0-5** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



**RHO** Cover for SDMO's generating sets, welding sets and water pumps