



PERFORM 3000 XL TB UK

PORTABLE POWER

Generating Sets Range PERFORM

PRODUCT ADVANTAGES

- · Entire group guaranteed 3 years
- · KOHLER air-cooled industrial engine
- Large Autonomy
- Good value for money
- Starting up facilitated thanks to the summer/winter positions

QUAD CLEAN AIR FILTER The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.

PERFORM 3000 XL TB UK

GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	13
75% cons. (I/h) *	1.30
75% Autonomy (h) *	10
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH270
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	208
Oil system capacity including filters (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

2 115V 16A sockets - circuit breaker + 1 socket 230V 16A - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	65
Width (cm)	51
Height (cm)	54
Dry Weight (kg)	47.50

PACKAGING

Packaging type	Box
Length (cm)	66
Width (cm)	52.50
Height (cm)	55
Weight (kg)	49.50
Pallet type	140/110
Number of box by pallet	12
Pallet height (cm)	178
weight of the packaged Pallet (kg)	610





This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety or users. Qualigen: commitment to safety and quality.





PERFORM 3000 XL TB UK

ACCESSORIES SUPPLIED



Funnel

RHO

User and maintenance manual

Floor maintaining slot

Ergonomic handle grip

OPTIONS



RKB1HD Trolley kit for the generating sets of 6kW or below



RKS1 Maintenance kit for KOHLER CH270 engine.



Cover for SDMO 's generating sets, welding sets and water pumps

